

marantz®

SR5009

AV RECEIVER WITH WI-FI & BLUETOOTH



PANDORA



The latest current feedback topology and Marantz's own new HDAMs are central elements of the new seven-channel SR5009. These technologies guarantee both power and detail in your surround sound experience. Bluetooth® and Wi-Fi are built-in so you can enjoy your digital files wherever they are stored. In addition, it provides networking DLNA 1.5 facilities for DSD & AIFF and Gapless HD audio streaming, Internet radio, SiriusXM™, Pandora®, Spotify Connect®, and AirPlay. It includes decoders for standard audio as well as for Dolby TrueHD and DTS-HD Master Audio. The SR5009 comes with no less than eight HDMI inputs one of which is on the front, and two outputs – making it immediately ready for 3D and even 4k 60Hz UHD resolution supporting 4:4:4 Pure Color. It easily handles the most demanding of scenes in action films, as well as offering excellent-quality music playback - thanks to the latest Marantz audio technologies and 100W (8ohms, 20 Hz - 20K Hz, THD 0.08%) from the seven amplifiers. Everything sounds clear, detailed, and alive with this set. As with many of this year's models, the SR5009 includes a smart ECO mode. To finish off, the SR5009 comes with a whole range of convenience features such as: Setup Assistant, auto calibration with Audyssey MultiEQ XT and Dynamic Volume Control; four Smart Select buttons, Multi-Room with multi-source flexibility; and "video-off" mode to ensure that you enjoy your music and movies in true dynamic Marantz style. It also has the specially developed Marantz Remote App for smartphone and tablet. All of which makes the SR5009 a true combination of style, power and ease.

Main Features

- Wi-Fi and Bluetooth built in
- Dolby TrueHD and DTS HD Master Audio
- 7ch discrete power amplifier, 100 W per channel (8ohms, 20 Hz - 20K Hz, THD 0.08%)
- Current Feedback circuitry with Marantz New HDAM
- Audyssey MultiEQ XT room calibration
- Latest HDMI version with 4k 60Hz 4:4:4 resolution
- 7+1 HDMI in / 2 out (4k 60Hz, 4:4:4, 3D, ARC, Deep Color)
- HDMI scaling 1080p, 4k 24/25/30Hz
- MP3, WAV, AAC, WMA, AIFF
- HD Audio streaming: FLAC 192/24, DSD, ALAC
- Gapless Playback
- Spotify Connect*, Flickr, SiriusXM, Pandora, and Internet Radio support
- Setup Assistant and advanced GUI
- Marantz Remote App for iOS and Android devices
- ECO mode

UPC

NA SR5009/U1B 6-99927-24135-3 Black

us.marantz.com



because music matters



marantz®

SR5009

AV RECEIVER WITH WI-FI & BLUETOOTH



FEATURES	SR5009
MULTICHANNEL SURROUND	
DTS HD Master / DTS 5.1 / DTS ES / DTS 96/24	• / • / • / •
Dolby Digital Plus / Dolby TrueHD / Dolby Digital EX / DPL IIz	• / • / • / •
Multichannel Stereo	•
Compressed audio Enhancer: MDAX2	•
NETWORK	
DLNA Certified	• (v1.5)
Lossy formats MP3 / WMA / AAC	• / • / •
Lossless formats FLAC / ALAC / WAV	• / • / •
DSD Streaming	• (2.8 MHz)
FLAC HD 192/24	•
WAV 192/24	•
ALAC 96/24	•
Gapless playback	• (FLAC, WAV, ALAC, DSD)
Photo streaming (JPEG)	•
AirPlay audio streaming	•
Windows PlayTo / Windows 8/RT compatible	• / •
Internet Radio (vTuner)	•
Spotify Connect *	•
Pandora	•
SiriusXM Internet Radio	•
Compatible with Remote APP for Smart Phones	Android/iOS
Ethernet / Wi-Fi	• / • (dual antenna)
OTHERS	
FM / AM Tuner	• / •
Current Feedback Topology	•
Hyper Dynamic Amplifier Modules (HDAM)	•
High grade audio components	•
Bluetooth	•
Auto speaker setup by microphone	Audyssey Mult EQ XT
Audyssey Dynamic EQ / Dynamic Volume	• / •
Video conversion	CVBS > HDMI; Comp > HDMI
Video processing	>1080p, 4k 24/25/30Hz
ISF Certification	•
HDMI path though on stand-by	•
3D video pass-through	•
Audio Return Channel	•
On Screen Display: Advanced GUI	•
GUI overlay on HDMI	•
Setup Assistant (English, French, Spanish)	•
Smart Select	4 presets
Variable cross over	•
Multi-room zones	2
Optimized Bass Redirection	•

INPUTS/OUTPUTS	
VIDEO	
Composite In / Out	2+1 / 1
Component In / Out	2 / 1
HDMI In / Out	7+1 / 2 (4k 60Hz, 4:4:4 bypass)
AUDIO	
Analogue In / Out	4+1 / 0
Digital Optical In	2
Digital Coaxial In	2
Multichannel Pre Out	• (7.2)
Subwoofer Out	2
Zone audio preout	•
7.1 multichannel input	•
OTHER	
Speaker A / B	•
Height speaker terminal	Speaker B or Height
Bi-amp drive (5.1 ch setting)	•
Multi-Room Speaker Terminal	Surround Back assignable
RS232 control	•
IR Flasher In	•
DC Trigger output	•
Marantz remote bus	•
Network: (IP-control / update)	• / •
Front Inputs: HDMI / USB	• / •
USB Audio / Made for iPod / Made for iPhone	• / • / •
SPECIFICATIONS	
Number of poweramps	7
Power Output per channel	
Maximum Power output per channel	200 W
6 ohm, 1 kHz, 0.7%, 2ch Drive	140 W
8 ohm, 20 Hz - 20 kHz, 0.08%, 2ch Drive	100 W
Audio Signal to Noise Ratio	98 dB
GENERAL	
System Remote Control	RC024SR
Power Consumption in W	650
Power Consumption No-Sound (ECO ...on/off) in W	45 / 75
Standby Consumption in W	0.2 (with CEC 0.5)
Maximum Dimensions (W x D x H) in inches	17.32 x 6.34 x 13.62
Weight in lbs.	22.71

Design and specifications are subject to change by Marantz without notice.

* This feature is not available in all countries.