

# marantz®



## MM7055 - Multichannel Main Amplifier

The MM7055 is the five-channel option in this year's extended line-up of main amplifiers. Based on the technology used in the MM8003 and using the exact same chassis, it delivers a thumping 140W rms into 8 ohm to each of the channels, while the ultra-wide bandwidth current feedback technology easily handles the highest SACD frequencies – this also makes it ideal for the high definition DTS Master Audio and Dolby TrueHD formats too. The result? Totally precise tonal and image balance, speed and dynamics. And on top of all that, you also get XLR audio inputs, DC triggers and a Marantz control bus system for remote on/off. This is power and convenience to take your breath away.

### MAIN FEATURES

- 5ch power amplifier
- 5x 140W (8ohm) / 5x 170W (6ohm)
- Current Feedback circuitry
- High performance power supply
- XLR inputs
- DC Trigger control inputs

because music matters



SPECIFICATIONS	MM7055	SPECIFICATIONS	
<b>FEATURES</b>		Power Output (8/6 Ohm RMS)	140/170 Watts
Channels	5	Power Output (8/6 Ohm DIN)	-
Current Feedback Topology	o	Power Output (8/6 Ohm IHF)	-
Phono EQ: Standard/Current Feedback/Constant Current Feedback	-/-/-	Bridged Power Output (8 Ohm RMS)	-
HDAM version	-	Frequency Response	8Hz-100kHz
Power Transformer: Toroidal/El	-/o	Total Harmonic Distortion	0.03%
High Grade Audio Components	o	Damping Factor	100dB
Customised Components	o	Input Sensitivity: MM	-
Symmetric PCB layout	-	Input Sensitivity: MC	-
Aluminium extrusion heatsink	o	Signal to Noise Ratio: MM/MC	-/-
Copper plated chassis	-	Input Sensitivity: High level	1.2V/22kohm
Tri-Tone Control (Bass/Mid/Treble)	-	Input Sensitivity: Balanced High level	2.4V/30kohm
Balance/Bass/Treble/Loudness	-/-/-/-	Signal to Noise Ratio: High level	105dB
<b>OTHER</b>		<b>GENERAL</b>	
Linear Drive Power Supply	o	Available colors: Gold/Silver/Black/Silver-Gold	-/-/o/-
BTL possibility	-	Metal Front Panel	o
Bi-Amp and Multichannel option	-	Power Consumption in W	440
Shottkey diodes	-	Standby Consumption in W	0.4
Input Buffer Amp (All inputs/CD only)	o/-	Auto Power off	o
Seperate solid heatsinks	-	Detachable Power Cable	o
System block shielding: copper/metal/none	-/-/-	Remote Control	-
Double layer bottom plate	-	System Remote Function	-
Source Direct	-	Maximum Dimensions (W x D x H) in mm	440x384x184.5
Power Amp Direct	o	Weight in kg	15.2
Standby mode	o		
<b>INPUTS/OUTPUTS</b>			
Phono Input: MM/MC	-/-		
Balanced In/Out	5/-		
Pre-Out/Main In	-/5		
Power Amp Direct In	o		
Gold Plated Chinch	-		
Speaker A/B	-		
Speaker terminal: Screw/Marantz/WBT	o/-/-		
Number of terminals	5		
Marantz remote bus	o		
Remote power control (Trigger In/Out)	o		
Flasher In/IR receiver In	o/-		
Headphone Out	-		