

ST7001

AM/FM/XM STEREO TUNER



The ST7001 continues the legendary Marantz tradition of tuner performance with a digitally-synthesized “front end” optimized for both high sensitivity and high selectivity. This makes the ST7001 a great choice for both urban and rural areas. The audio circuitry follows this same high-quality pattern with custom-selected parts in a meticulous layout to maximize signal quality while minimizing interference. In addition, the ST7001 boasts a wide variety of convenience features including 100-station programmability with custom naming to help you get to your favorite broadcasts easily. The sleep timer function lets you fall asleep to the station of your choice. The D-Bus connector and supplied remote control make this tuner a cinch to integrate with the most advanced custom designed systems.

- XM-Ready (Connect and Play)
- AM/FM Stereo Tuner
- Triple IR Code Sets
- Total 100 Station Pre-set Memory (10 groups x 10 Stations) for AM/FM
- Editable Station Name
- Discrete All XM channel codes
- Dual Analog Audio Outputs
- RS232C Connection for System Control
- Direct IR Flasher Input
- Detachable Power Code
- Aluminum Front panel
- Weekly Timer
- Sleep Timer
- Timer-controlled AC Outlet



FEATURES

HDAM	-
XM-Ready	•
Chassis	Metal
Customized Components	-
Preset Station Memory	100
Station Naming	•
Sleep Timer	•

IN/OUTPUTS

AUDIO	
Analog L&R OUT	2
D-Bus remote (RC-5) In/Out	•
FM Antenna	•
AM Antenna	•

GENERAL

Color	Black
Front Panel	Aluminum
Remote Control	Device Remote RC7001ST
Power Requirements	AC 120V 60Hz
Power Consumption	12W
Dimensions W x H x D (Inches)	17 ⁵ / ₁₆ " x 3 ¹ / ₁₆ " x 14 ³ / ₁₆ "
Weight (lbs.)	9.0

SPECIFICATIONS

TUNER SECTION FM	
Frequency Range	87.5 - 108.0MHz
S/N Ratio (Mono/Stereo)	74/68 dB
Distortion (Mono/Stereo)	0.2/0.3 %
Selectivity (Wide/Narrow)	50 dB
Usable Sensitivity	1.1 V
Stereo Separation	43 dB
TUNER SECTION AM	
Frequency Range	520 - 1710kHz
S/N Ratio	53 dB
Distortion	-
Sensitivity	18 V

marantz[®]
LIFE AMPLIFIED™

*All specifications, dimensions and weights are subject to change without notice. D&M Holdings, Marantz, Marantz America, Inc. or any of its subsidiaries will not assume any liability for errors in this spec sheet which may result in consequential errors being made by retail dealers, designers, custom installers, cabinet makers or end users, etc based upon information contained within this document.