

# marantz®

## ST-17 Reference Series Stereo Tuner

The Marantz ST-17 AM/FM Tuner continues our tradition of providing the ultimate performance as it incorporates a number of engineering and design innovations that make it ideal for receiving even weak FM broadcasts. Specifically tuned for crystalline reception, the ST-17 features a segmented power supply, careful internal component choice, short signal paths, and our exclusive HDAM output devices all housed in a rigid chassis that shields the interior from electromagnetic and vibration interferences. It is a tuner fully in the Marantz tradition and one of the best you can place in your system.



### FEATURES

Gyro-Touch Tuning	•
Dual Gate MOSFET	•
High Alternate Channel Selectivity	•
HDAM	•
Chassis	Metal
Customized Components	•
Preset Station Memory	60
Station Naming	•
Sleep Timer	•

### IN/OUTPUTS

#### AUDIO

Analog L&R OUT	1
D-Bus remote (RC-5) In/Out	•
FM Antenna	A/B
AM Antenna	•

### SPECIFICATIONS

#### TUNER SECTION FM

Frequency Range	87.5 - 108.0MHz
S/N Ratio (Mono/Stereo)	80/73 dB
Distortion (Mono/Stereo)	0.05/0.08 %
Selectivity (Wide/Narrow)	55/70 dB
Usable Sensitivity	1.0 $\mu$ V
Stereo Separation	55 dB

#### TUNER SECTION AM

Frequency Range	520 - 1710kHz
S/N Ratio	52 dB
Distortion	0.2 % (1kHz)
Sensitivity	35 dB

### GENERAL

Color	Gold
Front Panel	Aluminum
Remote Control	Device Remote RC-17ST
Power Requirements	AC 120V 60Hz
Power Consumption	8.5W
Dimension W x H x D (Inches)	18 $\frac{1}{8}$ " x 3 $\frac{1}{8}$ " x 12 $\frac{3}{16}$ "
Weight (lbs.)	15



\*All specifications, dimensions and weights are subject to change without notice. D&M Holdings, Marantz, Marantz America, Inc. or any of its subsidiaries will not assume any liability for errors within this document.