

# marantz®



## SR8012 11.2 CHANNEL NETWORK AV RECEIVER WITH HEOS MUSIC STREAMING TECHNOLOGY

With unparalleled Marantz performance, the new top-of-the-line SR8012 AV receiver is made for those wanting the ultimate audio and video experience. Fully symmetrical built, the amplifier features a single board design for its 11 identical amplifier channels, each delivering 205W per channel, for seamless surround sound integration.

### Highlights

### Your Benefits

11.2 channel AV Receiver with 205W per channel	Enough power to fill big rooms with renowned Marantz sound
Dolby Atmos and DTS:X (up to 7.1.4 or 9.1.2), Auro-3D	Immersive 3D sound with effects from overhead
Single board per channel power amplifier design; centrally mounted, oversized toroidal transformer; copper-plated chassis	High-end build-quality for the ultimate in audio performance
High performance 192kHz/32bit D/A converters for all channels	Highest resolution for music and movie sound
Audyssey MultEQ XT32, LFC, Sub EQ HT, Dynamic Volume and Dynamic EQ	Delivering the ultimate equalization for your individual room
Built-in WiFi with 2.4GHz/5GHz dual band support	Improved network stability especially in WiFi-crowded environments
HEOS Music Streaming Technology with HEOS App	Comfortable control options, almost unlimited music sources, and multi-room experience with additional HEOS products
Works with Amazon Alexa	Make use of ALEXA VOICE CONTROL
AirPlay, Bluetooth, Internet Radio, Spotify Connect, TIDAL, Deezer	Access to almost unlimited online music sources
Network Streaming: DSD (2.8/5.6MHz), FLAC, ALAC and WAV support	High Resolution audio streaming for HiFi enthusiasts
4K/60 Hz, 4:4:4, HDR and BT.2020, Dolby Vision compatible, HLG	Latest HDMI standard for future-proof compatibility
8 HDMI inputs (incl. 1 front) with full HDCP 2.2 support; 3 HDMI outputs (zone)	Plenty of inputs for your digital devices; different video in different rooms
eARC (Enhanced Audio Return Channel) via future firmware update	Allows 3D audio transmission from TV via HDMI audio return channel
Color-coded speaker terminals, Setup Assistant, Marantz AVR Remote App	Hassle-free installation, setup and operation
Advanced Multi-Room options; 11.2ch Pre-out; RS232 Control; Crestron Connected, IP-control	Audio and video in multiple rooms; ready for 3rd Party Home Automation systems



# because music matters

## SR8012

### 11.2 CHANNEL NETWORK AV RECEIVER WITH HEOS MUSIC STREAMING TECHNOLOGY



Design and specifications are subject to change by Marantz without notice.

FEATURES	SR8012
<b>MULTICHANNEL SURROUND</b>	
DTS HD Master / DTS:X / DTS Neural:X	• / • / •
Dolby TrueHD / Dolby Atmos / Dolby Surround	• / • / •
Auro-3D / Auromatic	• / •
Multichannel Stereo	•
Compressed audio Enhancer: MDAX2	•
Audyssey	MultEQ XT32 with LFC/Sub EQ HT
Audyssey Dynamic EQ / Dynamic Volume	• / •
Audyssey MultEQ Editor App support	•
<b>NETWORK / SOURCES</b>	
Network Audio Streaming	•
HEOS Multiroom integrated	•
Lossy formats MP3 / WMA / AAC	• / • / •
Lossless formats FLAC / ALAC / WAV	• / • / •
DSD Streaming	• (2.8 MHz / 5.6 MHz)
FLAC HD 192/24 / WAV 192/24 / ALAC 192/24	• / • / •
Gapless playback	• (FLAC, WAV, ALAC, DSD)
AirPlay audio streaming	•
Internet Radio (Tuneln)	•
Spotify Connect / Deezer / TIDAL / Napster / Soundcloud*	• / • / • / • / •
Compatible with Remote APP for Smart Phones	Android/iOS
Ethernet / Wi-Fi	• / • (dual antenna / dual band)
Network: (IP-control / update)	• / •
Front Inputs: HDMI / USB	• / •
USB Audio	•
Bluetooth	•
<b>HDMI</b>	
4K 60Hz 4:4:4 resolution / HDCP 2.2	• / •
eARC (Enhanced Audio Return Channel)	• (via Firmware Update)
Dolby Vision compatible / Hybrid Log Gamma (HLG)	• / •
HDMI pass through on stand-by	•
3D video pass through	•
Video conversion	CVBS / HDMI; Comp / HDMI
Videoprocessing and -scaling	1080p, 4K 60/50Hz

\* This feature is not available in all countries.

INPUTS/OUTPUTS	
<b>VIDEO</b>	
Composite In / Out	4+1 / 2
Component In / Out	3 / 1
HDMI In / Out	7+1 / 3 (2 main + 1 zone)
<b>AUDIO</b>	
Analog In / Out	6+1 / 0
Digital Optical In	2
Digital Coaxial In	2
Multichannel Pre Out	• (11.2 with 11.2 processing)
Zone audio preout	2
Subwoofer Out	2
7.1 Multichannel input	•
<b>SPECIFICATIONS</b>	
Number of poweramps	11
Power Output per channel	
8ohm, 1%, 1ch Drive	205 W
8ohm, 0.7%, 2ch Drive	175 W
8 ohm, 20 Hz - 20 kHz, 0.08%, 2ch Drive	140 W
Audio Signal to Noise Ratio	102 dB
<b>GENERAL</b>	
Available colors: Black	
System Remote Control	RC038SR
Power Consumption in W	780
Power Consumption No-Sound (ECO ...on/off) in W	65 / 110
Standby Consumption in W	0.2 (with CEC 0.5)
Maximum Dimensions (W x D x H) in IN	17.3 x 18.1 x 7.3 (440 x 460 x 185)
Weight in lbs	38 lbs 6 oz
<b>UPC</b>	
<b>NA</b>	SR8012/U1B 699927241551 Black

Sound United  
1 Viper Way  
Vista, CA 92081  
United States

The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by D&M Holdings Inc. is under license. Dolby, Dolby Atmos, and the double-D symbol are trademarks of Dolby Laboratories. DTS, the DTS in combination with the Symbol, DTS:X, and the DTS:X logo are registered trademarks or trademarks of DTS, Inc. in the United States and/or other countries. The Spotify software is subject to third party licenses found here: [www.spotify.com/connect/third-party-licenses](http://www.spotify.com/connect/third-party-licenses). Other trademarks and trade names are those of their respective owners. Marantz is a trademark or registered trademark of D&M Holdings, Inc.

\* All specs can be subject to change.