



marantz®

Product information

PM-11S2 PREMIUM INTEGRATED AMPLIFIER



This latest addition to the 11-Series Marantz Premium Range is packed with proven and advanced technologies from the SC-11 and the SM-11. Thanks to the massive shielded Toroidal transformer and customized components, it offers ultra-stable power output at 2x 100W 8 ohms and 2x 200W 4 ohms. Absolute signal integrity and very low signal to noise ratio is guaranteed, via the 3-stage construction which includes a pre-amplifier and a dual stage main-amplifier – plus an extra pre amplifier for Phono MM/MC. Key technologies include the latest Marantz Current Feedback HDAM SA3, as well as symmetrical and shortest signal paths to deliver dynamic sound and perfect stereo imaging. The chassis and rear panel are copper-plated to minimise signal-degrading EMI and offering low impedance ground potential at any point. All of which means that the PM-11S2 will leave you breathless.

Main Features

- 2x 100 Watts (8 ohm) / 2x 200 Watts (4 ohm)
- Current Feedback circuitry
- Toroidal transformer
- Full discrete 3 stage amplifier construction
- New HDAM-SA3 circuitry
- Copper plated chassis
- Power Amp direct
- MM/MC Phono input with HDAM
- Aluminum top cover

EAN

| | | |
|-----------|------------|---------------|
| EU | PM11S2/N1S | 4951035037362 |
| | PM11S2/N1G | 4951035037379 |
| UK | PM11S2/T1S | 4951035037386 |
| | PM11S2/T1G | 4951035037393 |

because music matters



marantz®

PM-11S2 PREMIUM INTEGRATED AMPLIFIER



| FEATURES | PM-11S2 |
|---|---------------|
| Channels | 2 |
| Current Feedback Topology | 0 |
| Linear Drive Power Supply | 0 |
| CCNE | 0 |
| Linear volume control | 0 |
| BTL Possibility | - |
| BI-AMP and Multichannel option | 0 |
| Power Transformer: Toroidal / EI | 0 / - |
| Choke input | 0 |
| Shottky diodes | 0 |
| HDAM version | SA3 |
| High Grade Audio Components | 0 |
| Customised Components | 0 |
| Phono EQ: Standard / Current Feedback / Constant Current Feedback | - / - / 0 |
| Input buffer amp (all inputs / CD only) | 0 / - |
| Symmetric PCB Layout | 0 |
| Aluminum extrusion heat sink | 0 |
| Separate Solid Heat Sinks | 0 |
| System block shielding: Copper / metal / none | 0 / - / - |
| Copper plated chassis | 0 |
| Double Layer Bottom Plate | 0 |
| Balance / Bass / Treble / Loudness | 0 / 0 / 0 / - |
| Source Direct | 0 |
| Power Amp direct | 0 |
| Standby Mode | - |

| INPUTS/OUTPUTS | |
|---|-----------|
| Audio Inputs | 6 |
| Phono Input: MM/MC | 0 / 0 |
| Audio Outputs | 2 |
| Balanced In/Out | 1 / - |
| Pre-out / Main-in | 1 / - |
| Gold Plated Cinch | 0 |
| Speaker A/B | 0 |
| Speaker Terminal: Screw / Marantz / WBT | - / - / 0 |
| Number of terminals | 4 |
| D-Bus | - |
| Floating Bus Control (3.5mm mono jack x2) | 0 |
| Remote Power Control (Trigger In/OUT) | - / - |
| Flasher in / IR Receiver IN | - / - |
| Headphone Out | 0 |

| SPECIFICATIONS | |
|--|--------------|
| Power Output (8/4 Ohm RMS) | 100/200W |
| Power Output (8/4 Ohm DIN) | 120/210W |
| Power Output (8/4 Ohm IHF) | 140/260W |
| Bridged Power Output (8 Ohm RMS) | - |
| Frequency Response | 5Hz-100kHz |
| Total Harmonic Distortion | 0,01% |
| Damping Factor | 100 |
| Input Sensitivity: MM | 2.8mV/47kohm |
| Input Sensitivity: MC | 270uV/100ohm |
| Signal to Noise Ratio: MM/MC | 87dB/78dB |
| Input Sensitivity: High level | 240mV/20kohm |
| Input Sensitivity: Balanced High level | 480mV/40kohm |
| Signal to Noise Ratio: High level | 96dB |

| GENERAL | |
|---|-----------------|
| Available colors: Gold/Silver/Black/Silver-Gold | 0 / 0 / - / - |
| Metal Front Panel | 0 |
| Power Consumption in W | 300 |
| Standby Consumption in W | - |
| Detachable Power Cable | 0 |
| Remote Control | RC001PM |
| System Remote Function | 0 |
| Maximum Dimensions (W x D x H) in mm | 440 x 367 x 105 |
| Weight in kg | 27.0 |

Design and specifications are subject to change by Marantz without notice.

because music matters

www.marantz.eu