

marantz®

DV6500 Progressive Scan Universal DVD Player



Even though there are more "universal" disc players every day, quality players are difficult to find. The DV6500 combines universality and quality in a uniquely Marantz fashion. First, the DV6500 handles movie DVDs, DVD-As, SACDs, conventional music CDs, recordable CD-Rs and CD-RWs, VCD 2.0 discs, MP3 and WMA audio discs, and JPEG-format picture discs! Then, the way the DV6500 handles these discs truly sets it apart. The Marantz audio tradition extends well into the 21st Century with internal Dolby Digital and DTS decoders. Six of the finest 192kHz/24-Bit digital-to-analog converters make everything you play sound exceptionally lifelike. And you can even shut off the DV6500's video circuitry completely for the purest audio signal path possible. Internal bass management circuits route DVD-A and SACD audio channels directly to the proper speakers. Video technology includes advanced 3:2 pull down circuitry and wide bandwidth video D/A converters for exceptional picture quality. Composite, S-Video, and component outputs? Progressive scan? Of course! We haven't forgotten conveniences either. There's an advanced on-screen display, parental controls, front panel menu operation, and a new hand-contoured remote. Connectivity options include audio and video outputs as well as a D-BUS connector for total system control. The three-year warranty shows our confidence and increases your peace of mind. Would you expect anything less from Marantz?

- Plays Back DVD-Video/Audio, SACD-Stereo/Multi-channel, DVD-R/RW, CD, CD-R/RW, SVCD, VCD, MP3, WMA and JPEG Discs
- Progressive Scan with 3:2 Pull Down Film Detection
- 54MHz/10-Bit Video D/A Converter
- 192kHz/24-Bit Audio D/A Converters
- Audio EX Mode (Video Off)
- Dolby Digital®/DTS Decoder
- On Screen Display
- Parental Control
- Menu Operation From Front Panel
- Discrete Power On/Off
- Component, S-Video, Composite Outputs
- 5.1 ch Analog Audio Output
- Stereo Analog Audio Output
- Digital Audio Outputs (coaxial, optical)
- D-BUS (RC-5 In/Out) Remote Connection
- Remote Control



DV6500

FEATURES

DTS Decoder	•
Dolby Digital Decoder	•
Disc Capacity	1
Progressive Scan	•
3:2 Pulldown	•
Playback Formats	DVD-V, DVD-A, SACD-Multi, SACD-Stereo, DVD-R/RW, VCD, CD, CD-R/RW, MP3, WMA, JPEG
Video DAC	54MHz/10-Bit
Audio DAC	192kHz/24-Bit
HDAM	-
Video Circuit Off	•
Display On/Off	•
Power Transformer	EI
Gold Plated Terminals	•
Chassis	Metal
Zero-Impedance Plate	-
Double Layered Bottom Plates	-
Front Panel Cursor Keys	•
Video Scaler	-
Bass Management	-
Lip Sync. (Digital audio delay)	-
Separate Power Supply for Audio	-

INPUTS/OUTPUTS

VIDEO

HDMI Out	-
Component Out	1
S-Video Out	1
Composite Out	1

AUDIO

Analog Out (RCA)	1
5.1ch Analog Out	1
Optical Digital Out	1
Coaxial Digital Out	1

OTHERS

External Control (RS232C)	-
D-Bus Remote (RC-5) In/Out	1 / 1

SPECIFICATIONS

Freq. Response (Digital Audio)	4Hz - 88kHz (DVD-Audio, fs: 192kHz)
S/N Ratio	115 dB
Dynamic Range	100 dB
THD (1kHz)	0.0045%

GENERAL

Color	Black
Front Panel	Aluminum
Remote Control	RC6500DV
Power Requirements	AC120V 60Hz
Power Consumption	12W
Dimensions W x H x D (Inches)	17 1/8" x 2 9/16" x 8 7/8"
Weight (lbs.)	4.9



*All specifications, dimensions and weights are subject to change without notice. D&M Holdings, Marantz, Marantz America, Inc. or any of its subsidiaries will not assume any liability for errors within this document.