

marantz®

SR7009

AV RECEIVER WITH WIFI & BLUETOOTH



The new SR7009 builds on last year's SR7008 with no less than nine amplifier channels, each with 200W of pure power. Imagine: nine strategically-located speakers with audio processing capabilities that go even further - handling up to 11.2 channels to fully support Audyssey DSX, DTS Neo:X 11.1, as well as the latest decoding technology Dolby Atmos® - you will be flooded with the absolute ultimate in surround sound sensation, as well as preparing your system for 3D sound. What's more, because we have also upgraded to Audyssey MultEQ XT32 / LFC Pro you get an even more accurate calibration of the speaker to guarantee that every seat in the room is a 'sweet spot' for audio. The SR7009 has WiFi and Bluetooth built-in and it supports Apple lossless, Gapless, FLAC HD 192/24 and even DSD and AIFF network streaming. Spotify Connect and AirPlay audio streaming are on board too. But we haven't changed everything. We've kept the staggering impact of audio quality, which is quite simply an intoxicating mix of effortless power, amazing detail and sensational depth: all thanks to the use of current feedback technology, HDAM pre-amplification and, of course, the 200W for each of those nine channels. Imagine enjoying this exceptionally superior audio performance for all your music and movie sources. The eight HDMI (4k/60Hz pass through / scaling) inputs and the two HDMI output sockets for the main room and a third dedicated for Multiroom application handle almost all of today's Ultra HD formats. The SR7009 also includes the ECO mode and Smart Select. And to get it all up and running effortlessly, there's a handy Setup Assistant. Enough said?

Main Features

- Wi-Fi and Bluetooth built in
- Dolby Atmos
- Dolby TrueHD and DTS HD Master Audio
- 9ch discrete power amplifier, 200 W per channel
- 11.2ch signal processing and 13.2 Pre-out (with 2 independent subwoofers)
- Current Feedback circuitry with Marantz New HDAM
- Audyssey MultEQ XT32, LFC, Pro ready
- Audyssey DSX; dts-Neo:X (11.1ch)
- Latest HDMI version with 4k 60Hz 4:4:4 resolution
- 7+1 HDMI in / 3 out (4k 60Hz, 4:4:4, 3D, ARC, Deep Color)
- HDMI scaling 1080p, 4k 50/60Hz
- MP3, WAV, AAC, WMA, AIFF
- HD Audio streaming: FLAC 192/24, DSD, ALAC
- Gapless Playback
- Spotify Connect*, Flickr, Internet Radio support
- Phono (MM) input
- Setup Assistant and advanced GUI
- Big trapdoor design; Aluminum front panel
- Marantz Remote App for iOS and Android devices
- ECO mode

EAN

EU	SR7009/N1B	4951035053096	Black
	SR7009/N1SG	4951035053102	Silver-Gold
UK	SR7009/T1B	4951035053096	Black
	SR7009/T1SG	4951035053102	Silver-Gold

www.marantz.eu



because music matters

SR7009

AV RECEIVER WITH WIFI & BLUETOOTH



FEATURES	SR7009
MULTICHANNEL SURROUND	
DTS HD Master / DTS 5.1 / DTS ES / DTS 96/24	• / • / • / •
Dolby Digital Plus / Dolby TrueHD / Dolby Digital EX / DPL IIz	• / • / • / •
Dolby Atmos	•
Audyssey DSX	•
dts-Neo:X (11.1ch)	•
Multichannel Stereo	•
Compressed audio Enhancer: MDAx2	•
NETWORK	
DLNA Certified	• (v1.5)
Lossy formats MP3 / WMA / AAC	• / • / •
Lossless formats FLAC / ALAC / WAV	• / • / •
DSD Streaming	• (2.8 MHz)
FLAC HD 192/24 / WAV 192/24 / ALAC 96/24	• / • / •
Gapless playback	• (FLAC, WAV, ALAC, DSD)
Photo streaming (JPEG)	•
AirPlay audio streaming	•
Windows PlayTo / Windows 8/RT compatible	• / •
Internet Radio (vTuner) / Spotify Connect *	• / •
Compatible with Remote APP for Smart Phones	Android/iOS
Ethernet / Wi-Fi	• / • (dual antenna)
CONVENIENT AND SOUND	
FM / AM Tuner	• / •
Current Feedback Topology	•
Hyper Dynamic Amplifier Modules (HDAM)	•
High grade audio components	•
Bluetooth	•
Auto speaker setup by microphone	Audyssey Mult EQ XT32 (Pro)
Audyssey Dynamic EQ / Dynamic Volume	• / •
Video conversion	CVBS > HDMI; Comp > HDMI
Video processing	>1080p, 4k 50/60Hz
ISF Certification	•
HDMI pass-through on stand-by	•
3D video pass-through / Audio Return Channel	• / •
On Screen Display: Advanced GUI	•
GUI overlay on HDMI	•
Setup Assistant (English, German, French, Spanish, Italian, Dutch, Swedish, Polish, Russian)	•
Smart Select	4 presets
Variable cross over	•
Multiroom zones	3
Optimized Bass Redirection	•

INPUTS/OUTPUTS	
VIDEO	
Composite In / Out	3+1 / 2
Component In / Out	3 / 1
HDMI In / Out	7+1 / 3 (2 main + zone)
AUDIO	
Analogue In / Out	5+1 / 0
Digital Optical In	2
Digital Coaxial In	2
Multichannel Pre Out	• (13.2)
Subwoofer Out	2
Zone audio preout	•
7.1 multichannel input	•
OTHERS	
Gold-plated terminals	•
Speaker A / B	•
Height speaker terminal	Speaker B or Height
Bi-amp drive (5.1 ch setting)	•
Multi-Room Speaker Terminal	Surround Back assignable
RS232 control	•
IR Flasher In	•
DC Trigger output	•
Marantz remote bus	•
Network: (IP-control / update)	• / •
Front Inputs: HDMI / USB	• / •
USB Audio / Made for iPod / Made for iPhone	• / • / •
SPECIFICATIONS	
Number of poweramps	9
Power Output per channel	
6 ohm, 1 kHz, 1%, 1ch Drive	200 W
6 ohm, 1 kHz, 0.7%, 2ch Drive	165 W
8 ohm, 20 Hz - 20 kHz, 0.08%, 2ch Drive	125 W
Audio Signal to Noise Ratio	98 dB
GENERAL	
Available colours: Black / Silver-Gold	• / •
System Remote Control	RC026SR
Power Consumption in W	710
Power Consumption No-Sound (ECO ...on/off) in W	65 / 110
Standby Consumption in W	0.2 (with CEC 0.5)
Maximum Dimensions (W x D x H) in mm	440 x 411 x 185
Weight in kg	13.8

* This feature is not available in all countries.

Manufactured under license from Dolby Laboratories. Dolby, Dolby Atmos, and the double-D symbol are trademarks of Dolby Laboratories. The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by D&M Holdings Inc. is under license. Other trademarks and trade names are those of their respective owners. Marantz is a trademark or registered trademark of D&M Holdings, Inc.

Design and specifications are subject to change by Marantz without notice.