

marantz®



## SR5013

### 7.2 CHANNEL AV RECEIVER WITH HEOS MUSIC STREAMING

The Marantz SR5013 7.2 channel AV receiver offers immersive home theater and high-resolution audio support. Enjoy multi-dimensional surround sound with the latest audio formats in Dolby Atmos, DTS:X and DTS Virtual:X. The SR5013 is fully compatible with the latest HDMI specifications, including 4K video, and lets you stream wireless music from your smart devices via Bluetooth, AirPlay2 or the HEOS app.

#### Highlights

- 7.2 channel discrete power amplifier, 100W per channel (8-ohm, 20Hz – 20kHz, 0.08% THD)
- 8 HDMI inputs — including one HDMI input on the front panel — with full HDCP 2.2 support, plus two HDMI outputs
- 4K/60 Hz full-rate pass-through, 4:4:4 color resolution, HDR and BT.2020, plus Dolby Vision compatibility and Hybrid Log-Gamma (HLG)
- Supports object-based audio formats Dolby Atmos, DTS:X and DTS Virtual:X processing
- Ability to decode high-resolution audio ALAC, FLAC and WAV lossless files up to 24-bit/192-kHz — plus DSD 2.8MHz and 5.6MHz tracks let you enjoy music exactly as the artist intended
- Marantz proprietary HDAM circuit boards for more detailed, dynamic sound
- Built-in HEOS wireless multi-room audio technology
- Amazon Alexa voice control via the HEOS Home Entertainment skill
- Stream the most popular music services — like Spotify, Pandora, Tunes, Deezer and many others — via Bluetooth, AirPlay 2 or the HEOS app
- Integrated Phono input to connect to your turntable
- Optimize your audio experience with Audyssey MultEQ XT, Dynamic Volume and Dynamic EQ for a seamless setup within your listening environment
- Setup assistant, advanced GUI and Marantz 2016 AVR remote app for an easy out-of-box experience
- Built-in Wi-Fi with 2.4GHz/5GHz dual band support (dual antenna)
- Advanced Custom Installation Support: Web interface, IP control, Creston Connected, Domotz Pro, IHJI



because music matters

# marantz®

## SR5013

### 7.2 CHANNEL AV RECEIVER WITH HEOS MUSIC STREAMING



Design and specifications are subject to change by Marantz without notice.

FEATURES	SR5013
<b>MULTICHANNEL SURROUND</b>	
DTS HD Master / DTS:X / DTS Neural:X	• / • / •
DTS Virtual:X	•
Dolby TrueHD / Dolby Atmos / Dolby Surround	• / • / •
Auro-3D / Auromatic	- / -
Multichannel stereo	•
Max number of processing (Preamp) channels	7.1
Audyssey	MultEQ XT
Audyssey Dynamic EQ / Dynamic Volume	• / •
Compressed audio enhancer: MDAX2	•
<b>NETWORK</b>	
HEOS Multi-room streaming / network audio streaming	• / •
Lossy formats: MP3 / WMA / AAC	• / • / •
Lossless formats: FLAC / ALAC / WAV	• / • / •
FLAC HD 192/24 / WAV 192/24 / ALAC 192/24	• / • / •
DSD audio streaming	up to DSD5.6
Gapless playback	• (FLAC, WAV, ALAC, DSD)
AirPlay audio streaming	• (AirPlay2 via FW update)
Internet Radio (Tuneln)	• (Tuneln)
Spotify connect / Deezer / TIDAL / Napster / Pandora / SiriusXM	• / • / • / • / • / •
Compatible with Remote app (iOS/Android)	Marantz 2016 AVR Remote
Ethernet / Wi-Fi	• / • (dual antenna/dual band)
Bluetooth	•
<b>HDMI</b>	
4K 60Hz 4:4:4 resolution / HDCP 2.2	• / •
eARC (Enhanced Audio Return Channel)	-
Analog to HDMI scaling	480i/576i up to 4K 30/25/24
HDMI to HDMI scaling	up to 4K 30/25/24
GUI overlay on HDMI	•
HDR / HLG / Dolby Vision	• (HDR10) / • / •
3D signal pass-through	•
HDMI pass-through in Standby Mode	•

<b>MULTIROOM / CI</b>		
HEOS multi-room integrated	•	
Multi-room zones	2	
Zone audio source: HDMI / Opt, Coax / Network, USB / Analog	- / - / • / •	
IP Control / RS232 Control / Web Control / App Control	• / • / • / •	
Domotz Pro / IHIJI	• / •	
<b>INPUTS/OUTPUTS</b>		
<b>VIDEO</b>		
Composite in/out	2+1 / 1	
Component in/out	2 / 1	
HDMI in/out	7+1 / 2	
<b>AUDIO</b>		
Analog In / Out	4+1 / -	
Phono (MM) in	•	
Digital in: Optical / Coaxial	2 / 2	
Multi-room out: Analog / Digital	1 / -	
Multichannel pre-out	• (7.2)	
Subwoofer out	2	
7.1 Multichannel input	•	
<b>OTHER</b>		
Speaker terminal: gold plated screw / regular screw	- / •	
<b>SPECIFICATIONS</b>		
Number of poweramps	7	
Number of speaker terminals	7	
Power output (8 ohm, 20 Hz - 20 kHz, 0.08% 2ch drive)	100 W	
Power output (8 ohm, 20 Hz - 20 kHz, 0.05% 2ch drive)	140 W	
Power output (6 ohm, 1 kHz, 1% 1ch drive)	180 W	
<b>GENERAL</b>		
System remote control	RC035SR	
Power consumption in W	650	
Power consumption no-sound (ECO on / off) in W	45 W / 75 W	
Standby consumption in W	0.2 (with CEC 0.5)	
Maximum dimensions w/o antenna: (W x D x H) in inches	17.3 x 13.3 x 6.3	
Weight in lbs	22	
<b>UPC</b>		
SR5013/U1B	Black	699927201654

Sound United LLC  
North America Regional Headquarters  
1 Viper Way  
Vista, CA 92081

The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by D&M Holdings Inc. is under license. Dolby, Dolby Atmos, Dolby Surround, Dolby Vision, and the double-D symbol are trademarks of Dolby Laboratories. DTS, the Symbol, DTS in combination with the Symbol, DTS:X, and the DTS:X logo are registered trademarks or trademarks of DTS, Inc. in the United States and/or other countries. The Spotify software is subject to third party licenses found here: [www.spotify.com/connect/third-party-licenses](http://www.spotify.com/connect/third-party-licenses). Other trademarks and trade names are those of their respective owners. Marantz is a trademark or registered trademark of D&M Holdings, Inc.