

marantz®

NR1606

SLIM DESIGN NETWORK A/V RECEIVER



Discover a thrilling new dimension in surround sound with the NR1606 A/V Receiver, which features Dolby Atmos® immersive surround decoding. With Dolby Atmos you'll experience the same revolutionary 3D surround sound found in premium movie theaters, with the ability to create an overhead surround soundfield that dramatically expands the sonic space. And, via a future firmware update, the NR1606 will be able to decode DTS:X™ soundtracks, which also deliver an immersive 3-dimensional soundspace. With 8 HDMI 2.0a inputs (including 1 conveniently located on the front panel), the NR1606 is equipped to handle 4K Ultra HD full rate 60Hz content, 4:4:4 Pure Color sub-sampling, and 21:9 aspect ratio pass-through as well as Hyper Dynamic Range (HDR) and BT.2020 pass-through. All 8 HDMI inputs are also HDCP 2.2 compliant, which is a requirement for 4K Ultra HD copy-protected content. Featuring high current discrete power transistors on all 7 channels, the slim-design NR1606 packs the same punch as larger models, delivering earth-shattering surround sound from 50W per channel. Enjoy your digital media files from wherever they are stored, thanks to Bluetooth® and Wi-Fi built in. The advanced networking facilities for audio streaming include Internet radio, AirPlay® and Spotify Connect® – as well as Gapless HD Audio and DSD streaming.

Main Features

- Wi-Fi and Bluetooth built in
- Dolby Atmos and DTS:X (ready)
- 7ch discrete power amplifier, 50 W per channel
- Audyssey MultEQ auto speaker setup and room calibration
- Latest HDMI 2.0a version with 4K 60Hz 4:4:4 resolution
- 7+1 HDMI in / 1 out (4K 60Hz, 3D, ARC, HDR, BT.2020)
- Full HDCP 2.2 support on all inputs
- Advanced Video Processing with scaling of analog and digital signals up to 4K
- MP3, WAV, AAC, WMA, AIFF
- HD Audio streaming: FLAC 192/24, DSD, ALAC
- Gapless Playback
- Spotify Connect, Pandora®, SiriusXM™*, Internet Radio support
- Setup Assistant and Advanced GUI
- AirPlay on board
- Marantz AVR Remote App for iOS and Android™ devices
- ECO mode
- Front L/R and Zone 2 Preouts
- C4 certified IP Control
- ISF Certification



us.marantz.com



because music matters

UPC

NA NR1606/U1B 6-99927-27095-7 Black

NR1606

SLIM DESIGN NETWORK A/V RECEIVER



FEATURES	NR1606
MULTICHANNEL SURROUND	
DTS HD Master / DTS:X / DTS Neural:X	• / • / •
Dolby TrueHD / Dolby Atmos / Dolby Surround	• / • / •
Multichannel Stereo	•
Compressed audio Enhancer: MDAx2	•
NETWORK	
DLNA Certified	• (v1.5)
Lossy formats MP3 / WMA / AAC	• / • / •
Lossless formats FLAC / ALAC / WAV	• / • / •
DSD Streaming	• (2.8 MHz)
FLAC HD 192/24	•
WAV 192/24	•
ALAC 96/24	•
Gapless playback	• (FLAC, WAV, ALAC, DSD)
AirPlay audio streaming	•
Windows PlayTo / Windows 8/RT compatible	• / •
Internet Radio (vTuner)	•
Spotify Connect / Pandora / SiriusXM*	• / • / •
Compatible with Remote APP for Smart Phones	Android/iOS
Ethernet / Wi-Fi	• / • (dual antenna)
OTHERS	
FM / AM Tuner	•
Bluetooth	•
Auto Speaker Setup by Microphone	Audyssey MultEQ
Audyssey Dynamic EQ / Dynamic Volume	• / •
HDMI Pass-Through on Stand-By	•
3D Video Pass-Through	•
Video Conversion	CVBS / HDMI; Comp / HDMI
Video processing and -Scaling	1080p, 4k 30 / 25 / 24Hz
ISF Certification	•
Audio Return Channel	•
On Screen Display	Advanced GUI
GUI overlay on HDMI	•
Setup Assistant (English, French, Spanish)	•
Smart Select	4 presets
Variable Cross Over	•
Optimized Bass Redirection	•

INPUTS/OUTPUTS

VIDEO	
Composite In / Out	3 / 1
Component In / Out	2 / 1
HDMI In / Out	7+1 / 1
AUDIO	
Analog In / Out	3 / 0
Digital Optical In	1
Digital Coaxial In	1
Multichannel Pre Out	• (2.2)
Zone Audio Preout	•
Subwoofer Out	2
OTHER	
Speaker A / B	•
Height Speaker Terminal	Speaker B or Height
Bi-Amp Drive (5.1 ch setting)	•
Multi-Room Speaker Terminal	Surround Back Assignable
Marantz Remote Bus	•
Network: (IP-control / Update)	• / •
Front Inputs: HDMI / USB	• / •
USB Audio / Made for iPod / Made for iPhone	• / • / •

SPECIFICATIONS

Number of Poweramps	7
Power Output Per Channel	
Maximum Power Output Per Channel	100 W
6 ohm, 1 kHz, 0.7%, 2ch Drive	70 W
8 ohm, 20 Hz - 20 kHz, 0.08%, 2ch Drive	50 W
Audio Signal to Noise Ratio	98 dB
GENERAL	
Available colors: Black	•
System Remote Control	RC024SR
Power Consumption in W	250
Power Consumption No-Sound (ECO ...On/Off) in W	30 / 40
Standby Consumption in W	0.2 (with CEC 0.5)
Maximum Dimensions (W x D x H) in inches	17.3 x 14.8 x 4.1
Weight in lbs.	18.7 lbs

Design and specifications are subject to change by Marantz without notice.

* This feature is not available in all countries.

* All specs can be subject to change.